

GUARDIAN® SERIES
AUTOMATIC STANDBY GENERATOR

8-13 kVA



Choose the #1 Selling Home Standby Generator Brand

Generac's Guardian® Series provides the automatic backup power you need to protect your home and family during a power outage. Connected to your existing LP or natural gas fuel supply, it kicks in within seconds of determining power loss—automatically—and runs for as long as necessary until utility power returns.

Control your power. Control your life.™

GUARDIAN SERIES FEATURES:



OHVI® ENGINE

Purpose-built for the rigors of generator use, and requires significantly fewer scheduled maintenance checkups than competitive engines.



EVOLUTION™ CONTROLLER

The next generation of intuitive controllers featuring a multilingual, two-line LCD text display with color-coded, backlit buttons.



TOOL-LESS FUEL CONVERSION

Easily switch between natural gas and LP fuels in the field without the need for tools.

8-13 kVA

(KILO VOLT AMPERE)



ADDITIONAL FEATURES:

8 - 13 kVA Guardian Series generators provide either essential circuit or whole-house coverage, depending on the transfer switch options:

- Generac's OHVI® engine is purpose-built for the rigors of generator use, and requires significantly fewer scheduled maintenance checkups than competitive engines.
- Sturdy, enclosure with RhinoCoat™ finish for superior weather protection, modeled to withstand 150 mph winds and with a fire rating that allows for installations as close as 18" to the home.
- Composite mounting pad is included, eliminating the need to pour a concrete base unless specified by local codes.
- External "at-a-glance" indicator lights offer an easy way to see generator status without opening the generator enclosure.
- The only standby generator certified for natural gas operation at 3.5" of water column to accommodate low-pressure areas.
- Tool-Less fuel conversion allows for easy switching between natural gas and LP fuels in the field without the need for tools.

SPECIFICATIONS

	8 kVA	10 kVA	13 kVA
Generator Only Model#	6269	6270	6271
Automatic Transfer Switch	100 and 200 Amp Non-Service Rated NEMA 3R Switches Available		
Rated AC Frequency	50 Hz		
Voltage (Single Phase)	220V		
Amps @ 240V LPG	36.4	45.5	59
Amps @ 240V NG	31.8	45.5	59
Engine/Alternator RPM	3000 / 3000		
Engine	OHVI / 530cc	OHVI / 992cc	
Fuel Consumption @ full load LPG - L/hr (gal/hr)	5.74 (1.52)	7.28 (1.92)	9.53 (2.52)
Fuel Consumption @ full load NG- m³/hr (ft³/hr)	3.91 (138)	5.52 (195)	6.37 (225)
db(A) at normal operating load	60		
Enclosure	Steel		
Enclosure Color	Bisque		
Warranty	3 yr. / 1000 hr. Limited Warranty		
Dimensions (L x W x H, in millimeters / inches)	1218 x 638 x 732 / 48 x 25 x 29		
Weight (lbs./kg)	175.4 / 387	197 / 435	214 / 471

International Dealer Service Network

Generac's commitment to service includes scheduled maintenance programs, warranty assistance and emergency service to ensure that Generac customers are never left powerless. The largest international dealer network has factory-trained technicians on staff and maintains large inventories of Generac parts, components and accessories. Find a dealer near you at generac.com.

GENERAC®